



ENDRESS

Power Generators

ESE 2006 DBS-GT ES

Order No. **230034**

Main features

Alternator type	synchron
Continuous Power 3~ [kVA/kW]	25,0/20
Nominal voltage [V]	220/127
Nominal Current [A]	66/66
Power factor cos (phi)	0,8
Frequency [Hz]	60
Protection Class [IP]	23

Engine

Engine Type	BRIGGS & STRATTON / 35 HP
Design	2-cylinder 4-stroke OHV
Displacement [ccm]	993
Output 3000 rpm	21,0
CO2 emissions [g / kWh]	825,56
Fuel	Petrol
Fuel tank capacity [l]	35
Fuel consumption @ 75% PRP [L/h]	7,5
Running time @ 75% PRP	4,7
Starting system	E-Start incl. battery
Sound power level LWA [db(A)]	106
Weight in kg ca.	245
Dimensions L x W x H [mm]	1100 x 700 x 890
Shockproof sockets	1x 277/480V 20A 1x 277/480V 30A 1x 277/480V 60A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

garantía alguna ni implícita ni expresa del rendimiento de un motor concreto.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2021-9-27

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de



ESE 2006 DBS-GT ES

Order No. 230034



Power Generators

Equipment features

Lack of oil automatic switch-off

Alternator overload protection

Briggs & Stratton OHV engines

Large fuel tank for long running times

Compound regulated high performance generators for 400 V

выразить любую гарантию работы конкретного двигателя.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2021-9-27

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

